

Softstarter
PSE – Die effiziente Baureihe
Bemessungswerte gemäß UL

Bemessungswerte für Drehstrommotoren – In-Line-Schaltung (Reihenschaltung)

Softstarter Typ	Motorleistung P (PS) und Volllaststrom FLA (A)				
	Max. FLA A	U _e 200 V/208 V PS	U _e 220 V/240 V PS	U _e 440 V/480 V PS	U _e 550 V/600 V PS
PSE18	18	5	5	10	15
PSE25	25	7,5	7,5	15	20
PSE30	28	7,5	10	20	25
PSE37	34	10	10	25	30
PSE45	42	10	15	30	40
PSE60	60	20	20	40	50
PSE72	68	20	25	50	60
PSE85	80	25	30	60	75
PSE105	104	30	40	75	100
PSE142	130	40	50	100	125
PSE170	169	60	60	125	150
PSE210	192	60	75	150	200
PSE250	248	75	100	200	250
PSE300	302	100	100	250	300
PSE370	361	125	150	300	350

